

SCENEMAKER 1216

DMX512 Lighting Controller

SCENEMAKER 1216 is a universal intelligent lighting controller. It allows you to manage up to 12 fixtures composed of 16 channels each (192 channels in total), and up to 184 programmable scenes. Six chases can contain up to 184 steps composed by the saved scenes (the steps) and in any order. Programs can be triggered by music, MIDI, automatically or manually. Its control surface hosts various programming tools such as 8 universal channel sliders, quick access scanner and scene buttons, as well as a LED display for easier navigation of controls and menu functions.



KEY FEATURES

12 Fixtures with 16 DMX Channels each; 192 Channels in total

23 banks of 8 programmable scenes, 184 scenes total

6 chases of 184 programmed scenes from 23 banks

Execute multiple chases simultaneously

8 Sliders x 2 Pages for direct control of channels

Auto Mode controlled by Speed and Fade Time

8-CH / 16-CH modes for Assigned or Reversed DMX channels

Master Blackout

Built-in microphone for music triggering

USB connection for LED Goose-neck Lamp (Not included)

LED Display for easy navigation of menus

MIDI control over banks, chases and Blackout

MORE SPECIFICATIONS

| | |
|--------------|-----------------------|
| Power Supply | DC 9V-12V, 500mA min. |
|--------------|-----------------------|

| | |
|-------------------------|-----------------|
| USB Lamp (not included) | 5V - 200 mA max |
|-------------------------|-----------------|

| | |
|-----------|---------------|
| Protocols | DMX-512 USITT |
|-----------|---------------|

| | |
|------------|-------------------------------|
| Data Input | Locking 3-pin XLR male socket |
|------------|-------------------------------|

| | |
|-------------|---------------------------------|
| Data Output | Locking 3-pin XLR female socket |
|-------------|---------------------------------|

| | |
|------------------------|------------------------------------|
| Data Pin Configuration | Pin 1 shield, Pin 2 (-), Pin 3 (+) |
|------------------------|------------------------------------|

| | |
|-------------------------|---------------|
| Controller Size (WxHxD) | 482x82x133 mm |
|-------------------------|---------------|

| | |
|-------------------|--|
| Net Weight 2.0 kg | |
|-------------------|--|

| | |
|---------------------------|----------------|
| Packing Dimension (WxHxD) | 560x135x185 mm |
|---------------------------|----------------|

| | |
|----------------------|--------|
| Packing Gross Weight | 2.6 kg |
|----------------------|--------|