

ADX-800 LINK

ACTIVE 2-CHANNEL DI-BOX & SPLITTER

ADX-800 LINK is a DI-Box (Direct Injection Box) that converts up to two unbalanced audio signals (e.g. electric and / or acoustic guitars and basses, line signals such as guitar preamps, keyboards, multi-effects, computers, etc.) in balanced signals with XLR connections. This allows not only to attenuate the interferences that normally the unbalanced cables collect in the medium-long distances, but also acts as a splitter with a maximum of 3 outputs for Channel1 (2 XLR outputs + 1 balanced ¼" TRS Jack). It can be powered either by the supplied power adapter, or through the + 48V Phantom power coming from the mixer. It is equipped with a 3-position input attenuator (0dB, 20dB, 40dB) - to adapt the preamp stage to all types of signals - and the lift ground switch, very useful in case of ground loop. ADX-800 LINK is essentially an indispensable tool on stage, in the rehearsal room and recording studio to solve problems for musicians, DJs and sound engineers.

ADX-800 LINK

8fd0bd40-6bec-4c21-9f46-0ea54511a71e.jpg

05d95ba7-1a49-480d-9ccb-60a48a644941.jpg

13466554-9704-4181-b81c-2d

PRODUCT DETAILS

KEY FEATURES

2 Channels DI-Box Operation

1 Channel Splitter function with max 3 Outputs

TRS 1/4" Jack Outputs

Balanced XLR Outputs

0/20/40dB Attenuation

Operable via external Power Adapter (supplied) or external Phantom Power

Ground Loop selector

SPECIFICATIONS

Frequency Response	10Hz-30KHz ± 1 dB
Max Input Level	15 dBu ± 1 dB
Noise Level	-65dBu
Attenuation Pad	0dB/-20dB/-40dB
Modes	2-Channel/Link
Phantom Power (In case of power from balanced XLR connection)	+48Vdc
Power Adapter (included)	12Vdc/100mA min.
Consumption	2.3mA
Unit Size	112x65x36 mm
Unit Weight	260g
Carton Size	130x150x40 mm
Carton Gross Weight	400g (including DI-Box and Power Adapter)