

PMX-4MKII

6-CHANNEL POWERED MIXER WITH EFFECT AND MP3 PLAYER

PMX-4 MKII is designed to be a powerful resource for live and educational purposes. The friendly user interface is one of the best features of this product and allows you to configure your sound device in a fast and easy way. The 6-Channel Active Mixer lets you plug microphones, instruments or any other audio equipment thanks to the XLR inputs on CH1-4, the ¼" Jack inputs on CH1-3, the stereo RCA inputs on CH4 and the 3mm jack input on Ch5/6 that allows you to plug a computer, a smartphone, a portable MP3 player etc.

PMX-4MKII

[1808b6f9-3e54-4484-9677-6f3a16e4458a.jpg](#)

[8f5d87b1-dc96-4679-989c-7c603c4ebdc0.jpg](#)

PRODUCT DETAILS

KEY FEATURES

6-Channel 200+200W powered mixer with effect and multimedia player

4 Mic/Line channel (CH1-4) with independent 2-band EQ and FX send bus with adjustable level

1 stereo channel (CH5-6) with 3mm Jack connector for tablets, computers and other multimedia devices

3-Band EQ on Master outputs

24bit digital Reverb/Delay with Level, Delay Time and Repeat adjustment

RCA Stereo TAPE In/Out for an external recorder/player

MP3 player with A-Type USB and SD-Card slot for 8GB max mass storage devices

200+200W @ 4ohm amplification

SPECIFICATIONS

System Type	Active Mixer with MP3 Player
Rated Power	100+100W @ 4ohm
Peak Power	200+200W @ 4ohm
Frequency Range	20Hz - 20KHz +/-3dB @ 1W Output to 8ohm speakers
Mixer	6-Channel Inputs (4 x Mono /Line, 1 x Stereo Line)
Input Impedance	Mic – 2Kohm (balanced) / 1kohm (unbalanced); Line – 10kohm; Tape IN – 47Kohm
Input Channel EQ	HIGH +/-15dB @ 12kHz; LOW +/-15dB @ 80Hz
3-Band EQ	Bass - Mid- Treble for Master Section
Stereo Monitor Out	1/4" Jack (TRS)
Speaker Outputs	2x 1/4" Jack mono
DSP	24-bit Delay/Reverb with Adjustable Level, Time and Repeat
Digital Delay	Time 140 – 342ms
Digital Player	USB A-Type (max 8Gb); SSD slot (max 8Gb)
AC Input	230 V – 50Hz
Fuse	T2A 250V
Dimensions (WxHxD)	475x120x227mm - 18.70x4.74x8.94in
Weight	7.2 Kg - 18.87 lbs.