ALCHEMIX 403 PRO

10 CHANNELS PROFESSIONAL MIXER WITH USB PLAYER, BT PLAYER, EFFECT, COMPUTER INTERFACE

ALCHEMIX 403 PRO

This versatile mixer series is packed with everything you need to take your sound to the next level. With 10 channels (featuring 4 mic inputs and 3 stereo line inputs), it’s built for both small gigs and mid-sized events. Enjoy 48V phantom power and a 75Hz low-cut filter on all mic inputs, ensuring clean and crisp sound.

Customize your mix with the 3-band EQ, two Aux Sends with pre/post selection, and plenty of flexibility with Mute, PFL-AFL, Sub, and L-R Assignments. For creative control, the built-in 24-bit, 16-preset professional effects engine lets you add the perfect touch to your sound, plus a handy Tap Tempo button.

Need to play some tracks? The Bluetooth and USB player give you full control with separate volume and assignments.

On top of that, you’ve got a high-quality USB soundcard for seamless 48kHz, 24-bit audio, plus a 7-band graphic EQ, 2 AUX returns, and soundcard playback control for even more fine-tuned adjustments and DAW integration. Whether you're mixing live or recording, this mixer has you covered with top-tier functionality and pro-level performance.

a88e724f-a92d-4f01-bda2-78f3afac2530.jpg

40e8c25c-d326-4ec0-a378-314bc6dd6023.jpg

Bluetooth

Phantom Power

USB Player

PRODUCT DETAILS

KEY FEATURES

10 channels (4 mic inputs + 3 Stereo Line Inputs)
48V and 75Hz Low-cut on all Mic inputs
3-Band EQ, 2 Aux Send with Pre/Post selection
1 Effect bus, Mute, PFL-AFL, Sub and L-R Assignment
Bluetooth and USB Player with separate volume and assignments
USB Input/Output Sound Card (48kHz – 24-bit)
24-bit High-Quality Digital Effects with 16 adjustable presets and Tap Tempo button
7 Band graphic EQ, 2-Ch AUX Return, 2-Ch Subgroup, Soundcard playback control

SPECIFICATIONS

Configuration Channels	4 Mono Mic/Line, 3 Stereo Line
Max Input Level	Mic +10dBu / Line +22dBu
Max Output Level	XLR +22dBu, TRS +20dBu
Input Gain	Mic/Line +8~+54dB, Stereo Line 0~+10dB
Master Meter	-32dB to CLIP
Channel Meter	Signal LED Indicator
Frequency Response	20Hz to 22kHz ±1dB
CMRR (Mic 1kHz)	>75dB
THD+N (Total Harmonic Distortion+Noise)	<0.05%
Channel EQ	+/-15dB (High 12kHz), +/-15dB (Mid 2.5kHz), +/-15dB (Low 80Hz)
USB Audio	USB 2.0 / 2-Channel In/Out @ 48kHz
Supported Audio Formats	MP3/WAV/FLAC
DSP FX Processor	16 Presets, 24-bit/48kHz
Bluetooth	V 5.1
Power Requirements	100-240V~50/60Hz
Fuse Type	T1.6A H250V
Product Size (WxDxH)	334 x 345 x 86 mm
Product Weight	3.45 kg
Packing Size (WxDxH)	373 x 443 x 130 mm
Packing Gross Weight	3.9 kg