



GO-SOUND POCKET MIC

Kit Bodypack, Headset, and Lavalier Mic for GO-SOUND AMW Speakers

The Go-Sound Pocket Mic is an optional set including a VHF bodypack transmitter, a lavalier microphone, and a headset microphone. It is intended for all of those owners of SOUNDSATION GO-SOUND AMW Active Speakers who need total freedom of movement during their sessions.



KEY FEATURES

Compatible with GO-SOUND 8AMW / 10AMW / 12AMW / 15AMW

VHF Transmission with SMD Technology

175MHz VHF Frequency (NOTE

Before purchasing this product, make sure that the wireless microphone frequency of your Go-Sound 8-10 AMW – or at least one of the two frequencies for Go-Sound AMW 12-15 AMW – is 175MHz)

Plug and play setup

30m ideal distance (without obstacles)

Simple and lightweight bodypack

Lightweight Headset with cardioid electret capsule

Tie Microphone with clip and omni-directional electret capsule

MORE SPECIFICATIONS

Carrier Frequency VHF - 175,00MHz

Transmitter Power 10mW

Modulation Type FM

Deviation 37KHz

Spurious Emission > 30dB

Continuous Using 7 hours

Frequency Stabilization Automatic calibration

Dynamic Range > 90dB

Total Harmonic Distortion

Frequency Response 40Hz~15KHz ±3dB

Input Connector 1/8" mono Jack (without thread)

Knobs Mic Volume

LED Red (battery-low)

Battery Voltage 3V (2x1.5V AA Battery)

Headset Microphone Cardioid electret capsule

Headset Connector 1/8" Mini-Jack (90° without thread)

Lavalier Microphone Omni-directional electret capsule

Lavalier Connector 1/8" Mini-Jack (without thread)