

WF-DA100 KIT

KIT COMPOSED BY UHF WIDEBAND ACTIVE DIRECTIONAL ANTENNA, AND TRIPOD STAND

WF-DA100 is a directional antenna for professional receiving within UHF range. Optimized for 400MHz~1000MHz, it has a 4~6dBi high directional characteristic which is ideal for the environment that needs specific direction usage. The most unique feature is connected to receivers directly. Besides, it is built with a 15dB high gain booster specifically for long distance receiving, compensate for coaxial cable connected to the receiver caused. The power of the amplifier is derived from the coaxial cable connected to the antenna divider or to UHF receivers kit includes an adjustable tripod stand.

WF-DA100 KIT

ca30d114-637a-48e5-91f8-7ac2779f9771.jpg

PRODUCT DETAILS

SPECIFICATIONS

Bandwidth	400MHz - 1000MHz
Gain	4-6 dBi
Amplifier Gain	15±1dB
VSWR (Voltage Standing Wave Ratio)	2:1
3dB beam width	75°vertical polarization plane and horizontalpolarization
Power consumption	200mW
Antenna connector	BNC female
Size(WxHxD)	31x3x30,5cm
Packing Size(WxHxD)	36,9x5,7x36,1cm
Weight	0,45kg
Packing Weight	0,76Kg