

WF-V21PPA

DUAL VHF PLUG AND PLAY WIRELESS MICROPHONE WITH 2 BODYPACK AND HEADSET MICS (213.0 MHZ - 215.5 MHZ)

WF-V21 is the answer to all those who need a reliable, high-quality sound, and easy to use set of wireless microphones. Ideal in educational, Portable Sound, Public Address, and DJ contexts, the WF-V21 impresses with its brilliant and warm sound, thanks to the quality of components and the capsule designed for all application.

WF-V21PPA

[fe23671f-18c0-45d1-b9de-a98967e5d8ab.jpg](#)

[87d82dca-b850-4b7b-b813-425d82fa2cad.jpg](#)

PRODUCT DETAILS

KEY FEATURES

VHF Transmission with SMD Technology

2 available Pairs of Frequencies in VHF Band

Simple user Interface for plug and play setup

30m ideal distance (without obstacles)

2 Strong yet lightweight bodypack

Professional and Lightweight Headsets with high-sensibility dynamic cardioid capsules

SPECIFICATIONS

Carrier Frequency	VHF 200 - 215.3 MHz
Operating Frequencies	213.0 MHz - 215.5 MHz
Frequency Stabilization	Automatic calibration
Dynamic Range	> 90dB
Total Harmonic Distortion	< 0.5%
Frequency Response	40Hz - 16kHz / ± 3 dB
Packing Dimensions (WxHxD)	436 x 104 x 324 mm
Packing Gross Weight	2.0 kg
Receiver Power Supply	DC12V, 500mA
Receiver Consumption	< 4W
Signal/Noise Ratio	> 95dB
Receiving Sensitivity	10dBuV
De-Emphasis	75uS
Audio Output Level	Balanced 400mV; Unbalanced 400mV
Receiver Size (WxHxD)	211 x 43 x 115 mm (antennas not incl.)
Antenna Length	110 mm (min.) 430 mm (max.)
Net Weight	0.295 kg
Transmitter Power	10mW
Modulation Type	FM
Deviation	37KHz
Battery Voltage	3V (2x1.5V AA-Type Batteries)
Continuous Using	7 hours
Pocket Trans. Dimensions (WxHxD)	62 x 103 x 30 mm
Antenna (W/DxH)	Ø3 x 9 mm
Pocket Transmitter Net Weight	0.132 kg (batteries included)