

ADX-500

ULTRA LOW NOISE ACTIVE DI BOX

The SOUNDSATION ADX-500 ACTIVE BOX is an electronic device that converts an unbalanced audio signal into a balanced signal . You can connect unbalanced input devices like an electric bass, a guitar or a keyboard. The balanced line is less sensitive to electromagnetic interferences and has a better S/N ratio. In this way it is possible to achieve a good performance in case of long distances as well. For instance, it is possible to connect your instrument to a distant mixer maintaining a good quality signal. The ADX-500 is highly recommended for sound engineers and stage/studio performers.

ADX-500

[1ca59149-809a-4d84-8dcc-77e11a22c847.jpg](#)

PRODUCT DETAILS

KEY FEATURES

Converts unbalanced input signal in balanced output signal

Input jack 6,3mm unbalanced

Unbalanced XLR Female Input

Unbalanced 6,3mm Jack Monitor/Link output

Pad 0dB - 20 dB

Balanced XLR Male Output

Ground lift switch

9V battery operated

SPECIFICATIONS

Frequency response	30Hz-20KHz
Maximum input level	0 ±20dB
Noise level	= 105 dBU
Power Requirement	AC 20~48V
Battery	9V blockcell 6LR91
Dimension	145X125X59mm
Weight	700 g